

Absolute Time Interface

ATI-RG401-S



Overview

4Links' Absolute Time Interface (ATI) enables all the 4Links test units, in a test system, to be synchronized to an accurate "Time of Year". Timing measurements can be made with any number of units, all sharing a common time reference. The ATI also has a single activated SpaceWire port which outputs a 1 pulse per second SpaceWire Time Code. The Time-code Generator (TG) enables the ATI to output up to four independent and configurable Time Codes, all synchronized to Time of Year.

Features

- To receive an IRIG-B00x signal from a separate IRIG receiver, and use it to maintain a common time reference for a number of 4Links SpaceWire test equipment units;
- To provide a time synchronisation signal for most members of the 4Links EtherSpaceLink family of SpaceWire test equipment;
- To transmit a SpaceWire Time Code once per second to a SpaceWire network;
- To provide status information via its front-panel display.
- To be configurable using its front-panel switch.

Product Facts

- Products conform to ECSS-E-ST-50_12C (31st July 2008)
- Receive speeds in the range from 1.2Mb/s to more than 400Mb/s
- User selected transmit speeds, available from 1Mb/s up to more than 400Mb/s
- Standard 9-way Micro-miniature D-type SpaceWire socket connectors
- IRIG B002 (100pps, pulse-width code, no carrier, BCD Time of Year)
- Any number of units in a synchronization chain, not exceeding 50 metres length of all cables
- Synchronization to IRIG, plus/minus 500ns or better
- Synchronization is achieved using eight SMA connectors on the back of each unit

Options

TG: Timecode Generator - provides up to four independent and configurable SpaceWire Time Codes.

Ordering information

One Active Port ATI-RG401-S

Legal notice and disclaimer: Copyright ©2018 4Links Limited, all rights reserved. The name 4Links and the accompanying device are registered as a Trademark in the European Union and in the United States of America. The name SpaceWire was originated by the European Space Agency whose rights are acknowledged, and 4Links makes no claim to the word SpaceWire being a 4Links trademark. The information supplied in this document is believed to be accurate at the date of issue. 4Links reserves the right to change specifications or to discontinue products without notice. 4Links assumes no liability arising out of the application or use of any information or product, nor does it convey any licence under its patent rights or the rights of others. Products from 4Links Limited are not designed, intended, authorised or warranted to be suitable for use in life-support devices or systems. 4Links Limited is registered in England and Wales, with Company Number 3938960.